



SIP Conference Phone with Four Wireless Mics

Quick start guide

businessphones.vtech.com



Model: VCS754-WM

Congratulations

on purchasing your new VTech product.


For support, shopping, and everything new at VTech, visit our website at businessphones.vtech.com.

Install the wireless mic battery




- Risk of explosion! Batteries should not be exposed to excessive heat such as bright sunlight or fire.
- Use only the supplied battery.
- Risque d'explosion! Le bloc-piles ne doit pas être exposé à la chaleur excessive telle que la lumière du soleil ou au feu.
- N'utilisez que la pile incluse.

1. Plug the battery connector securely into the socket inside the battery compartment. Insert the battery (with the label **THIS SIDE UP** facing up) into the battery compartment.
2. Slide the battery door until it clicks into place.



3. Place the wireless mics into the charging cradles until they are flush.



note

- Charge the battery for 8 hours before use. The mic indicator light is orange when the battery is charging, and turns off when the battery is fully charged.
- If the wireless mic unit becomes warm when the battery is charging, it is normal.

Register the wireless mic

You should register your new wireless mic to the base unit following the instructions below.

As part of this process, all existing, broken, or lost wireless mics will be deregistered first. Then, the base unit will re-register the four wireless mics that are placed into the charging cradles.

During registration, incoming calls will not have any audio after being answered. Audio connection will resume when registration is complete.

To deregister the wireless microphones:

1. Place the new wireless mic and the other three wireless mics into the charging cradles.
2. When the base unit has no active calls, press **MENU**.
3. On the Main Menu, highlight **User Settings** and then press **SELECT**.
4. On the User settings menu, highlight **Wireless microphone** and then press **SELECT**.
5. On the Wireless microphone menu, highlight **Deregister** and then press **SELECT**. The screen displays **Deregister all wireless microphones?**
6. Press **Yes**. The wireless mics enter the deregistration mode, and the screen displays **Deregistering...** and then

Wireless microphones are deregistered. The microphone status indicators flash red and green to indicate they are awaiting registration.

After deregistration is complete, you must register each microphone.

To register the wireless microphones:

1. On the Wireless microphone menu, with **Register** highlighted, press **SELECT**. The screen displays **Registering...** and then **Registration succeeded**. The base plays a confirmation tone. The registered mic stops flashing red and green.
2. Repeat step 1 for the remaining wireless microphones.

note

- If a microphone fails to register, the base unit will display **Registration failed**. Remove the unregistered wireless mic from the charging cradles and place it back in. Repeat steps 1 to try the registration process again.
- All wireless mics should always be kept on the charging cradles during the registration process. Any wireless mic that was deregistered but not put into the charging cradle will remain deregistered after the above operations.
- Status indicators on the wireless mics flash red and green alternately during registration.
- To cancel registration, press **Cancel**.



Specifications are subject to change without notice.
© 2015–16 for VTech Communications, Inc.
All rights reserved. 06/16. VCS754-WM_QSG_V3

Compliance

FCC Part 15

This equipment has been tested and found to comply with the requirements for a Class B digital device under Part 15 of the Federal Communications Commission (FCC) rules. These requirements are intended to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications to this equipment not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2)

this device must accept any interference received, including interference that may cause undesired operation. Privacy of communications may not be ensured when using this telephone.

To ensure safety of users, the FCC has established criteria for the amount of radio frequency energy that can be safely absorbed by a user or bystander according to the intended usage of the product. This product has been tested and found to comply with the FCC criteria. The wireless mic may be safely held against the ear of the user. The telephone base shall be installed and used such that parts of the user's body other than the hands are maintained at a distance of approximately 20 cm (8 inches) or more.

This Class B digital apparatus complies with Canadian requirement CAN ICES-3 (B)/NMB-003(B)

Cet appareil numérique de la classe B est conforme à la norme NMB-003 du Canada.

Industry Canada

Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Privacy of communications may not be ensured when using this telephone.

The term "IC:" before the certification/registration number only signifies that the Industry Canada technical specifications were met.

This product meets the applicable Innovation, Science and Economic Development Canada technical specifications.